



POWER BRIGHT
YOUR LEADER IN POWER SOLUTIONS

MODEL
PW400-12

SPECIFICATION SHEET

400 Watt 110 Volt AC, 12 Volt DC Power Inverter

This inverter plugs into your cigarette lighter to power laptops, cell phone chargers and other small electronic devices in your vehicle!



This unit has the following features:

- 400 watts continuous power
- 800 watts peak power
- Provides 3.3 Amps
- Anodized aluminum case provides durability
- Built-in Cooling Fan
- External, Replaceable 40 Amp spade-type Fuse
- 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch
- Cigarette lighter plug



Output Wave Form	Modified Sinewave
No-load draw	< 0.16 amp (12V)
Efficiency	Up to 90%
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible at 10.6 VDC
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	Two 3-Prong
Warranty	1 year
Inverter weight	2.6 lbs
Dimensions (W x H x D)	5 x 2 x 7.4 in.

MODEL
PW400-12
SPECIFICATION SHEET

www.PowerBright.com
© 2010 PowerBright . All rights reserved